

## Addressable Intelligent manual call point

\*Coding method: It can realize online coding with the help of a coder and without the necessity of disassembling the bus (however, the equipment must be powered off). Address codes 1 to 324 are available for selection.

\*Telephone jack: Two-wire fire telephone jack (equipped with a standard 6.3 single-track audio connector).

\*Starting part: A plastic pressing sheet that may be used repeatedly. It can be manually reset with a special tool after being pressed.

\*Starting mode: Press the pressing sheet manually.

\*Matched host machine: fire alarm control panel (such as CFT-MN300)

Place of Origin	Guangdong, China (Mainland)
Brand Name	PROYU
Model Number	PY-CFT-960
Executive standard	GB19880-2005
Operating voltage	24V (pulse modulation)
Operating current	<300uA (in the monitoring status); <2mA (in the action status)
Normally open contact Capacity	0.1A/30VDC
Weight	About 120g
Wiring method	non polar two-bus system (L1, L2)
Indoor, temperature	-10°C~+50°C;
Relative humidity	≤95% (40°C±2°C, without condensation)

