

## Hohe DB 8-Zoll-Alarmglocke

Merkmale und Vorteile:

- \* Kompatibel mit allen konventionellen Brandmelde
- \* Schalttafel
- \* Hohe Schallpegel bis zu 95 dB
- \* Einfache Installation baracket enthalten
- \* Stahlmaterial

|                              |   |
|------------------------------|---|
| Ursprungsort                 | Guangdong, China (Festland)                                   |
| Markenname                   | PROYU   |
| Modellnummer                 | PY-JL188-8  |
| Produktname                  | Alarmglocke   |
| Größe                        | 200x200x65mm  |
| Betriebstemperaturbereich    | -10 ° C bis 50 ° C  |
| Luftfeuchtigkeit bei Betrieb | 10% bis 93% relative Luftfeuchtigkeit,<br>nicht kondensierend |
| Systemspannung (nominal)     | 24 VDC (16 V ~ 30 V DC)                                       |
| Alarm Current                | 70 mA bei 24 VDC  |
| Alarm Schallintensität       | Mindest 95dB  |





## ALARM BELL

### Install item

1. Before install please detail reading the specification.
2. Install the bell according to fire standard height.
  - Firstly open the bell cover screw, then screw the bell cover, according to the direction of the figure 1.
3. Firstly put the plastic base to fix on the bell, pay attention the strike pin to enter same, see figure 2.
4. Switch on\*\*according to red line, the type of the stack line with on\*\*\*, switch on DC24V power.
5. Finally installed bell cover, and tighten up a screw to fix.