- 16 zone conventional fire alarm control panel
- * Four to Sixteen Style B (Class B) Initiating Device Circuits (IDCs).
- * All zones accept two-wire smoke detectors and any normally-open contact devices.
- * Zones 1 16 configured as general alarm zones.

* All circuits are power-limited and supervised, meeting the latest ULC requirements using fuseless technology.

- * Two built-in, Style Y (Class B) Notification Appliance (Signal) Circuits (NACs).
- * NACs may be programmed: Silenceable. Non-Silenceable.
- * Auto-Silence (program 5 to 20 minutes).
- * 1.25 amps of NAC power.
- * 3.0 amps of total system power.
- * Alarm, Trouble and Supervisory, Form-C relay standard.
- * 24-volt operation.
- * Resettable four-wire smoke detector power @ 500 mA.
- * Non-resettable power @ 500 mA.

* Integral battery charger capable of charging up to 18 AH batteries (batteries over 4 AH require use of the external battery backbox, or ULC listed equivalent).

- * One-man walk-test programmable for silent or audible test.
- * Disable/Enable control per IDC.
- * Reverse polarity protection.
- * Control buttons:

Mode/Test/ACK (Acknowledge) Alarm Silence/Reset

