

Fingerprint reader/scanner PY-F11

Parameters:

Fingerprint Capacity	1500 Templates
ID Card Capacity	10,000
Transaction Capacity	N/A
Hardware Platform	ZEM500
Sensor	Optical Sensor
Algorithm Version	Finger V9.0
Communication	RS232/485, TCP/IP
Access Control Interface for	3rd party electric lock, exit button, alarm
Wiegand Signal	Output
Optional Functions	Other rf cards
Display	N/A
Power Supply	12V DC
Operating Temperature	0 °C- 45 °C
Operating Humidity	20%-80%
Dimension	66.4*153.5*61mm (W*H*D)
Net Weight	0.46kg
OEM	Yes
SDK	Available
Multi languages	Available
bell scheduling	Built in
Serial and Ethernet ports	Build in

Application: home, office, school, government, building , or other purpose.



