

## Smart Home Villa RFID Video Door Phone Intercom System PY-V101-FD

### Feature:

- ◆ Outdoor camera with metal case and rain cover, classic humanized design
- ◆ Hands-free indoor monitor, acrylic frontplate, elegant design, 10.1inch TFT color screen with clear image
- ◆ Function: intercom, monitor, two way talk back and unlock
- ◆ IR nightvision, and communicate between indoor monitor to indoor monitor
- ◆ Color brightness and Volume adjustable
- ◆ Choose multi-ringtone by yourself
- ◆ Can be 1 to 1,2,3,4 or 2 to 1,2,3,4 system, meet your different requirement
- ◆ International standard design and production, 4wire, easy install, DIY
- ◆ Application: Villa, Home, Office etc

### Technical Parameters:

- ◆ Audio distortion rate  $\geq 50\text{mW}$
- ◆ Talking Time: 90s, monitor time: 30s
- ◆ Input Power Supply: AC100-240V 50Hz - 60Hz
- ◆ Output Power Supply: AC14.5V 1200mA
- ◆ Frequency response:  $300\sim 3400\text{Hz} \pm 3\text{dB}$
- ◆ Working Voltage:  $\text{DC}15\text{V} \pm 10\%$
- ◆ Resolution: 200,000 pixels
- ◆ Consumption: static state  $\leq 0.5\text{W}$ , current state  $\leq 10\text{W}$
- ◆ Installation: outdoor camera flush mounting, indoor monitor surface mounting
- ◆ Indoor monitor dimension:  $273\text{mm} \times 181\text{mm} \times 22\text{mm}$
- ◆ Outdoor Camera dimension:  $96\text{mm} \times 174\text{mm} \times 45\text{mm}$   
Installation dimension:  $80\text{mm} \times 147\text{mm} \times 36\text{mm}$

### Wiring requirement:

- ◆ 30M: RVV4 X 0.5 mm, ,
- ◆ 50M: RVV4 X 0.75 mm
- ◆ 100M: RVV4 X 1.0 mm

**Note: when connect more monitor, to next indoor monitor with RVV5**