

بوصة جرس الانذار DB 8 ارتفاع

الميزات والفوائد:

* متوافق مع جميع إنذار الحريق التقليدية

* لوحة التحكم

و dB * مستوى صوت عالي يصل إلى 95

* baracket وشملت التركيب وسهلة

* مادة الصلب

مكان المنشأ	(وقوانغدونغ، والصين (البر الرئيسي
اسم العلامة التجارية	PROYU
نموذج رقم	PY-JL188-8
اسم المنتج	جرس الانذار
أبعاد	200x200x65mm
نطاق درجة حرارة التشغيل	-10 ° C إلى 50 ° C
تعمل مجموعة الرطوبة	الرطوبة النسبية 10% إلى 93%، دون تكاثف
(نظام الجهد (الاسمية	24 VDC (16V ~ 30VDC)
إنذار الحالية	70 24 @ مللي أمبير VDC
إنذار شدة الصوت	و dB الحد الأدنى 95





ALARM BELL

Install Item

1. Before install please detail reading the specification.
2. Install the bell according to fire standard height.
 - Firstly open the bell cover screw, then screw the bell cover, according to the direction of the figure 1.
3. Firstly put the plastic base to fix on the bell, pay attention the strike pin to enter same, see figure 2.
4. Switch on**according to red line, the type of the shock line with on***, switch on DC24 power.
5. Finally installed bell cover, and tighten up a screw to fix.