

Высокая DB 8-дюймовый Набат

Особенности и преимущества:

- * Совместимость со всеми обычными пожарной сигнализации
- * Панель управления
- * Высокая уровень звука до 95 дБ
- * Простая установка baracket включены
- * Сталь Материал

Место происхождения	Гуандун, Китай (материк)
Бренд	PROYU
Номер модели	PY-JL188-8
Наименование	Набат
Размеры	200x200x65mm
Диапазон рабочих температур	-10 ° C до 50 ° C
Влажность при эксплуатации	10% до 93% относительной влажности, без конденсации
Система напряжение (номинальное)	24 В постоянного тока (16V ~ 30V)
Ток тревоги	70 мА при 24 В постоянного тока
Звуковая сигнализация Интенсивность	Минимальная 95dB





ALARM BELL

Install Item

1. Before install please detail reading the specification.
2. Install the bell according to fire standard height.
 - Firstly open the bell cover screw, then screw the bell cover, according to the direction of the figure 1.
3. Firstly put the plastic base to fix on the bell, pay attention the strike pin to enter same, see figure 2.
4. Switch on**according to red line, the type of the stack line with on***, switch on DC24V power.
5. Finally installed bell cover, and tighten up a screw to fix.